Setting up Google Home Voice Control to Sitara Lighting Control

- 1. Set up your **Avi-on App account** and **add your Sitara devices**, including a **Sitara Remote Gateway** device (needed to connect to a Google Home Device).
- 2. Installed the Google Home App and create a Google account (if you don't already have one).
- 3. Open the **Google Home App** and follow the following steps
 - a. Navigate to the App 'Home Control' page
 - b. Tap the "+" button to move to the 'Add' page
 - c. Select 'Set Up device', then the 'Works with Google' option
 - d. On the 'Add devices' page, tap the magnifying glass and search for 'Avi-on Smart Home' and select it
 - e. Enter your **Avi-on** account details (not your Google account)
 - f. Select Allow when prompted with 'Google will request access to control your devices'
 - g. Your Avi-on account is now paired with your Google Home account
 - h. Follow the prompts on your Google Home App to Add your devices to Rooms, if desired

That's it! Start using Google Home with your Sitara System!

Example Google Home Voice Commands

| Google Home Voice Command | Action |
|---------------------------------|---|
| "Hey Google, turn on" | Turns device, Group or Scene ON |
| "Hey Google, turn off" | Turns device, Group or Scene OFF |
| "Hey Google, dim up" | Dims Device or Group UP 25% from the previous |
| | setting |
| "Hey Google, dim down" | Dims Device or Group DOWN 25% from the |
| | previous setting |
| "Hey Google, dim to 50%" | Dims Device or Group to 50% light level |
| "Hey Google, set to Warm White" | Changes the Device or Group CCT to Warm White |
| | (Note: Applies to Pierlite Bluetooth downlights only) |
| "Hey Google, set to Cool White" | Changes the Device or Group CCT to Cool White |
| | (Note: Applies to Pierlite Bluetooth downlights only) |
| "Hey Google, Lights ON" | Turns all the Devices / Groups in the account ON |
| "Hey Google, Lights OFF" | Turns all the Devices / Groups in the account OFF |